



T-8

MINI FM TRANSCEIVER
With USB Type-C interface



MAIN FEATURE

- ▶ Frequency Range: 446-446.2MHz
- ▶ 16 Memory Channels
- ▶ Output Power 0.5W
- ▶ Support non-standard CTCSS/DCS
- ▶ Side keypad assignment
- ▶ Flashlight
- ▶ Vox Function



T-8

MINI FM TRANSCEIVER
With USB Type-C interface



MAIN FEATURE

- ▶ Frequency Range: 446-446.2MHz
- ▶ 16 Memory Channels
- ▶ Output Power 0.5W
- ▶ Support non-standard CTCSS/DCS
- ▶ Side keypad assignment
- ▶ Flashlight
- ▶ Vox Function

SPECIFICATION

GENERAL		TRANSMIT PART	
Frequency Range	446-446.2MHz	RF Power	0.5W
Operating Temperature	-20°C~+60°C	Modulate Mode	F3E
Frequency Combination	Phase lock frequency synthesize	Max. Freq. Deviation	≤5K
Frequency Stability	±2.5ppm	Remain Wave Radiation	<-60dB
Memory Channel	16 Channels	Transmitting Current	≤1000mA
Working voltage	DC 3.7V	RECEIVE PART	
Battery capacity	2000mAh Li-ion Battery	Sensitivity	<0.25μV(12dB SINAD)
Antenna Impedance	50Ω	Squelch Sensitivity	<0.20μV
Operating Mode	Simplex of co-frequency or alien frequency	Intermodulation Antijamming	50dB
Dimension	89×49×31mm (without volume knob)	Audio Power output	500mW
Weight	150g (Include Battery Pack)	Receiving Current	≤100mA
		Squelch Standby	20mA

Notice: Saving your presence, no additional notice will be sent if specification changes because of technology improving.